

# GM-SERIES

STEREO MIXER WITH 16 DSP EFFECT

# NTS



**GM-8FX** : 8 Channel Mixer (4 Mono / 2 Stereo) with 16 DSP Effect  
**GM-12FX** : 12 Channel Mixer (4 Mono / 4 Stereo) with 16 DSP Effect

## TECHNICAL SPECIFICATION

- Insert point on mono input
- 3 band EQ on all input
- 1 Aux send for external effects and monitoring
- Peak LED on all input
- LOW CUT switch on mono input
- MUTE and SOLO switch on all input
- Built in 16 program digital effect
- Voice canceller function
- 7 band graphic EQ
- +48V phantom power supply

### MAIN SPECIFICATION :

Channel Mic/Line ..... 8 CH : 4 Mono/2 Stereo [GM-8FX]  
..... 12 CH : 4 Mono/4 Stereo [GM-12FX]

Total Harmonic Distortion .....  $\leq 0.05\%$   
Frequency Response ..... 5Hz-50kHz, +/-3dB  
S/N Ratio .....  $\geq -103\text{dB}$   
Max Output ..... 4V Max  
Input Sensitivity : Mic ..... -60dB  
: Line ..... -40dB  
: Effect Return ..... -40dB  
: Aux in ..... -40dB  
: Tape in ..... -40dB  
Mono Channel EQ : High ..... +/-15dB, 12KHz  
: Mid ..... +/-15dB, 2.5KHz  
: Low ..... +/-15dB, 80Hz  
Stereo Channel EQ : High ..... +/-15dB, 12KHz  
: Mid ..... +/-15dB, 2.5KHz  
: Low ..... +/-15dB, 80Hz  
Power Requirement ..... AC 220V/50Hz

<http://www.nts-solution.com>

All features & specifications are subjected to change without notice.

# NTS

บริษัท เอ็นทีเอส อิเล็กทรอนิกส์ โซลูชั่น จำกัด  
NTS Electronic Solution Co., Ltd.

1439-1441 ถนนเจริญนคร แขวงบางลำภูล่าง เขตคลองสาน กรุงเทพฯ 10600

โทรศัพท์: 0-2438-7023-4, 0-2437-7639 โทรสาร: 0-2437-1897

<http://www.nts-solution.com> E-mail: [nts@nts-solution.com](mailto:nts@nts-solution.com)

1439-1441 Charoennakorn Rd. Banglumpoolang Klongsan Bangkok 10600, Thailand

Tel: (+66-2) 438-7023-4, (+66-2) 437-7639 Fax: (+66-2) 437-1897